CHP-6G18G-4040-S is a complete solid state microwave power amplifier module that features high efficiency, high output power and wide dynamic range. It is based on advanced microwave device technology and provides long-term reliability and high ruggedness.

Features:

6.0-18.0 GHz ultra-broadband

Psat:10W Typ

High efficiency, High reliability and ruggedness

Built-in protection circuits

Electrical Specifications:

Frequency: 6.0-18.0 GHz Power Gain: 40 dB Min Gain Flatness: ±5 dB Tvp Power Output: +40 dBm Typ Harmonics: -10 dBc Typ Non Harmonics Spurious: -60 dBc Typ Input Power: +5 dBm Max Input Return Loss: 10 dB Min Output Return Loss: 10 dB Typ DC Voltage: +27 to +29 V DC Supply Current: 2.5 A Typ

Mechanical Specifications:

Parameter	Specification
Dimensions WxHxD	5.91X3.54X0.79 inch
RF Connectors In/Out	SMA-F
DC Connector	J30J
Cooling	External Heatsink

DC Connector PIN Assignment:

Pin	Description	Specification
1-3	+28V	+28 V DC
6-9	GND	GND
4-5	NC	+28 V DC

Environmental Ratings:


Temperature: 0ºC to +50 ºC Operating

-20 °C to +65 °C Non-Operating

Vibration: MIL-STD-202F, Method 204D Cond. B
Altitude: MIL-STD-202F, Method 105C Cond. B
Temperature Cycle: MIL-STD-202F, Method 107D Cond. A

SOLID STATE HIGH POWER AMPLIFIER CHP-6G18G-4040-S				
DRAWN:	DWG NO.:	REV CODE: Rev.1.0	CONNPHY Microwave Inc.	
CHECKRD:	DATE: 14/05/15	SHEET: 1 OF 2	www.connphy.com sales@connphy.com	
ISSUED:	SIZE: A	SCALE : N / A	Notes: SPEC ARE SUBJECT TO CHANGE WITHOUT NOTICE.	

Mechanical Outline (Inches):



Environmental Ratings:

Temperature: 0ºC to +50 ºC Operating

-20 °C to +65 °C Non-Operating

Vibration: MIL-STD-202F, Method 204D Cond. B
Altitude: MIL-STD-202F, Method 105C Cond. B
Temperature Cycle: MIL-STD-202F, Method 107D Cond. A

SOLID STATE HIGH POWER AMPLIFIER CHP-6G18G-4040-S				
DRAWN:	DWG NO.:	REV CODE: Rev.1.0	CONNPHY Microwave Inc.	
CHECKRD:	DATE: 14/05/15	SHEET : 2 OF 2	www.connphy.com sales@connphy.com	
ISSUED:	SIZE: A	SCALE : N / A	Notes: SPEC ARE SUBJECT TO CHANGE WITHOUT NOTICE.	